



²⁾ 厚度 < 1 mm : 導角 = 20°

倒角和 d1 的關係

d1 [mm]:	Ø 1-6	Ø 6-12	Ø 12-30	Ø > 30
f [mm]:	0.3	0.5	0.8	1.2

尺寸 [mm]

d1	d1- 公差 ³⁾	d2	b1 h13	產品型號
1.5		3.0	2.0	GSM-0103-02
2.0		3.5	3.0	GSM-0203-03
2.5	+0.014	4.5	5.0	GSM-02504-05
3.0	+0.054	4.5	3.0	GSM-0304-03
3.0		4.5	5.0	GSM-0304-05
3.0		4.5	6.0	GSM-0304-06
4.0		5.5	4.0	GSM-0405-04
4.0	+0.020	5.5	6.0	GSM-0405-06
4.5	+0.068	6.0	8.0	GSM-0406-08
4.0		7.0	5.5	GSM-0407-05
5.0		6.0	4.6	GSM-0506-046
5.0	+0.010	6.0	5.0	GSM-0506-05
5.0	+0.040	6.0	7.0	GSM-0506-07
5.0		7.0	5.0	GSM-0507-05
5.0	+0.020	7.0	7.0	GSM-0507-07
5.0	+0.068	7.0	8.0	GSM-0507-08
5.0		7.0	10.0	GSM-0507-10
6.0		7.0	6.0	GSM-0607-06
6.0		7.0	12.0	GSM-0607-12
6.0	+0.010	7.0	17.0	GSM-0607-17
6.0	+0.040	7.0	17.5	GSM-0607-17.5
6.0		7.0	19.0	GSM-0607-19
6.0		8.0	1.5	GSM-0608-015
6.0		8.0	2.5	GSM-0608-025
6.0	+0.020	8.0	3.0	GSM-0608-03
6.0	+0.068	8.0	4.0	GSM-0608-04
6.0		8.0	5.0	GSM-0608-05
6.0		8.0	5.5	GSM-0608-055

³⁾ 按壓組裝後 測試方法 ▶ 頁碼 57

產品代碼

類型 尺寸 [mm]

G S M - 0103-02

iglidur® 材質	型號 S	公制	內徑 - Ø d1	外徑 - Ø d2	長度 b1
-------------	------	----	-----------	-----------	-------

i 尺寸符合 ISO 3547-1 標準
且提供特殊尺寸

inch 也可選用英制尺寸
▶ 見頁碼 1402

d1	d1- 公差 ³⁾	d2	b1 h13	產品型號
6.0		8.0	6.0	GSM-0608-06
6.0		8.0	8.0	GSM-0608-08
6.0	+0.020	8.0	9.5	GSM-0608-09
6.0	+0.068	8.0	10.0	GSM-0608-10
6.0		8.0	11.8	GSM-0608-11
6.0		8.0	13.8	GSM-0608-13
7.0	+0.013	8.0	10.0	GSM-0708-10
7.0	+0.049	8.0	19.0	GSM-0708-19
7.0		9.0	8.0	GSM-0709-08
7.0	+0.025	9.0	9.0	GSM-0709-09
7.0	+0.083	9.0	10.0	GSM-0709-10
7.0		9.0	12.0	GSM-0709-12
8.0		9.0	5.0	GSM-0809-05
8.0	+0.013	9.0	6.0	GSM-0809-06
8.0	+0.049	9.0	8.0	GSM-0809-08
8.0		9.0	12.0	GSM-0809-12
8.0		10.0	5.0	GSM-0810-05
8.0		10.0	6.0	GSM-0810-06
8.0		10.0	6.8	GSM-0810-07
8.0		10.0	8.0	GSM-0810-08
8.0		10.0	10.0	GSM-0810-10
8.0	+0.025	10.0	12.0	GSM-0810-12
8.0	+0.083	10.0	13.8	GSM-0810-13
8.0		10.0	14.0	GSM-0810-14
8.0		10.0	15.0	GSM-0810-15
8.0		10.0	16.0	GSM-0810-16
8.0		10.0	18.0	GSM-0810-18
8.0		10.0	20.0	GSM-0810-20

iglidur® G | 產品範圍

軸襯套 (型號 S)

尺寸 [mm]

d1	d1- 公差 ³⁾	d2	b1 h13	產品型號
8.0	+0.025	10.0	22.0	GSM-0810-22
8.0	+0.083	10.1	25.0	GSM-0810-25
8.0	+0.040 +0.130	12.0	9.0	GSM-0812-09
9.0	+0.013	10.0	12.0	GSM-0910-12
9.0	+0.049	10.0	16.0	GSM-0910-16
9.0	+0.025	11.0	6.0	GSM-0911-06
9.0	+0.083	11.0	20.0	GSM-0911-20
10.0		11.0	6.0	GSM-1011-06
10.0		11.0	7.0	GSM-1011-07
10.0	+0.013	11.0	10.0	GSM-1011-10
10.0	+0.049	11.0	20.0	GSM-1011-20
10.0		11.0	25.0	GSM-1011-25
10.0		11.0	30.0	GSM-1011-30
10.0		12.0	4.0	GSM-1012-04
10.0		12.0	4.5	GSM-1012-045
10.0		12.0	5.0	GSM-1012-05
10.0		12.0	6.0	GSM-1012-06
10.0		12.0	7.0	GSM-1012-07
10.0		12.0	8.0	GSM-1012-08
10.0	+0.025	12.0	9.0	GSM-1012-09
10.0	+0.083	12.0	10.0	GSM-1012-10
10.0		12.0	12.0	GSM-1012-12
10.0		12.0	14.0	GSM-1012-14
10.0		12.0	15.0	GSM-1012-15
10.0		12.0	17.0	GSM-1012-17
10.0		12.0	20.0	GSM-1012-20
10.0		13.0	13.5	GSM-1013-13
10.0	+0.025	14.0	10.0	GSM-1014-10
10.0	+0.115	14.0	20.0	GSM-1014-20
10.0	+0.040 +0.130	16.0	10.0	GSM-1016-10
12.0		13.0	4.7	GSM-1213-047
12.0	+0.016	13.0	10.0	GSM-1213-10
12.0	+0.059	13.0	12.0	GSM-1213-12
12.0		13.0	15.0	GSM-1213-15
12.0		14.0	4.0	GSM-1214-04
12.0		14.0	5.0	GSM-1214-05
12.0		14.0	6.0	GSM-1214-06
12.0	+0.032	14.0	8.0	GSM-1214-08
12.0	+0.102	14.0	10.0	GSM-1214-10
12.0		14.0	12.0	GSM-1214-12
12.0		14.0	14.0	GSM-1214-14
12.0		14.0	15.0	GSM-1214-15
12.0		14.0	20.0	GSM-1214-20

d1	d1- 公差 ³⁾	d2	b1 h13	產品型號
12.0		14.0	25.0	GSM-1214-25
12.0	+0.032	15.0	6.0	GSM-1215-06
12.0	+0.102	15.0	22.0	GSM-1215-22
12.0	+0.050	16.0	10.0	GSM-1216-10
12.0	+0.160	16.0	20.0	GSM-1216-20
13.0		15.0	7.0	GSM-1315-070
13.0		15.0	7.5	GSM-1315-075
13.0		15.0	10.0	GSM-1315-10
13.0		15.0	15.0	GSM-1315-15
13.0		15.0	20.0	GSM-1315-20
13.0		15.0	25.0	GSM-1315-25
14.0		16.0	3.0	GSM-1416-03
14.0	+0.032	16.0	6.0	GSM-1416-06
14.0	+0.102	16.0	8.0	GSM-1416-08
14.0		16.0	10.0	GSM-1416-10
14.0		16.0	12.0	GSM-1416-12
14.0		16.0	15.0	GSM-1416-15
14.0		16.0	20.0	GSM-1416-20
14.0		16.0	25.0	GSM-1416-25
14.0		16.0	45.0	GSM-1416-45
15.0	+0.016	16.0	10.0	GSM-1516-10
15.0	+0.059	16.0	15.0	GSM-1516-15
15.0		17.0	4.0	GSM-1517-04
15.0		17.0	10.0	GSM-1517-10
15.0		17.0	12.0	GSM-1517-12
15.0		17.0	15.0	GSM-1517-15
15.0		17.0	20.0	GSM-1517-20
15.0		17.0	25.0	GSM-1517-25
16.0		18.0	5.5	GSM-1618-055
16.0		18.0	8.0	GSM-1618-08
16.0	+0.032	18.0	10.0	GSM-1618-10
16.0	+0.102	18.0	12.0	GSM-1618-12
16.0		18.0	13.5	GSM-1618-13.5
16.0		18.0	15.0	GSM-1618-15
16.0		18.0	20.0	GSM-1618-20
16.0		18.0	25.0	GSM-1618-25
16.0		18.0	30.0	GSM-1618-30
16.0		18.0	38.5	GSM-1618-38.5
16.0		18.0	50.0	GSM-1618-50
17.0		19.0	15.0	GSM-1719-15
18.0	+0.016	19.0	15.0	GSM-1819-15
18.0	+0.059	20.0	6.0	GSM-1820-06
18.0	+0.032	20.0	10.0	GSM-1820-10
18.0	+0.102	20.0	12.0	GSM-1820-12

³⁾ 按壓組裝後 測試方法 ▶ 頁碼 57

尺寸 [mm]

d1	d1- 公差 ³⁾	d2	b1 h13	產品型號	d1	d1- 公差 ³⁾	d2	b1 h13	產品型號
18.0		20.0	15.0	GSM-1820-15	24.0		27.0	20.0	GSM-2427-20
18.0		20.0	20.0	GSM-1820-20	24.0	+0.040	27.0	24.0	GSM-2427-24
18.0		20.0	25.0	GSM-1820-25	24.0	+0.124	27.0	25.0	GSM-2427-25
18.0	+0.032	20.0	34.0	GSM-1820-34	24.0		27.0	30.0	GSM-2427-30
18.0	+0.102	20.0	38.0	GSM-1820-38	25.0	+0.020	26.0	23.0	GSM-2526-23
18.0		20.0	45.0	GSM-1820-45	25.0	+0.072	26.0	25.0	GSM-2526-25
18.0		22.0	30.0	GSM-1822-30	25.0		28.0	12.0	GSM-2528-12
19.0		22.0	6.0	GSM-1922-06	25.0		28.0	15.0	GSM-2528-15
19.0	+0.040	22.0	28.0	GSM-1922-28	25.0		28.0	20.0	GSM-2528-20
19.0	+0.124	22.0	35.0	GSM-1922-35	25.0		28.0	24.0	GSM-2528-24
20.0	+0.020	21.0	20.0	GSM-2021-20	25.0		28.0	25.0	GSM-2528-25
	+0.072				25.0		28.0	30.0	GSM-2528-30
20.0		22.0	3.0	GSM-2022-03	25.0		28.0	35.0	GSM-2528-35
20.0		22.0	8.0	GSM-2022-08	25.0		28.0	50.0	GSM-2528-50
20.0		22.0	10.5	GSM-2022-105	26.0	+0.040	30.0	16.0	GSM-2630-16
20.0		22.0	15.0	GSM-2022-15	27.0	+0.124	30.0	5.0	GSM-2730-05
20.0		22.0	20.0	GSM-2022-20	28.0		32.0	10.5	GSM-2832-105
20.0		22.0	22.0	GSM-2022-22	28.0		32.0	12.0	GSM-2832-12
20.0		22.0	28.0	GSM-2022-28	28.0		32.0	15.0	GSM-2832-15
20.0		22.0	30.0	GSM-2022-30	28.0		32.0	20.0	GSM-2832-20
20.0		22.0	47.0	GSM-2022-47	28.0		32.0	23.0	GSM-2832-23
20.0		23.0	4.5	GSM-2023-045	28.0		32.0	25.0	GSM-2832-25
20.0		23.0	10.0	GSM-2023-10	28.0		32.0	30.0	GSM-2832-30
20.0		23.0	15.0	GSM-2023-15	28.0	+0.065	35.0	19.0	GSM-2835-19
20.0		23.0	20.0	GSM-2023-20	28.0	+0.195	35.0	28.0	GSM-2835-28
20.0		23.0	24.0	GSM-2023-24	29.0	+0.040	33.0	6.0	GSM-2933-06
20.0	+0.040	23.0	25.0	GSM-2023-25		+0.124			
20.0	+0.124	23.0	30.0	GSM-2023-30	30.0		31.0	5.0	GSM-3031-05
20.0		23.0	35.0	GSM-2023-35	30.0	+0.020	31.0	12.0	GSM-3031-12
22.0		24.0	8.0	GSM-2224-08	30.0	+0.072	31.0	30.0	GSM-3031-30
22.0		24.0	10.0	GSM-2224-10	30.0		34.0	12.0	GSM-3034-12
22.0		24.0	12.0	GSM-2224-12	30.0		34.0	15.0	GSM-3034-15
22.0		24.0	15.0	GSM-2224-15	30.0		34.0	20.0	GSM-3034-20
22.0		24.0	17.0	GSM-2224-17	30.0		34.0	24.0	GSM-3034-24
22.0		24.0	20.0	GSM-2224-20	30.0	+0.040	34.0	25.0	GSM-3034-25
22.0		24.0	30.0	GSM-2224-30	30.0	+0.124	34.0	30.0	GSM-3034-30
22.0		24.0	48.0	GSM-2224-48	30.0		34.0	35.0	GSM-3034-35
22.0		25.0	15.0	GSM-2225-15	30.0		34.0	40.0	GSM-3034-40
22.0		25.0	20.0	GSM-2225-20	30.0		34.0	52.5	GSM-3034-525
22.0		25.0	25.0	GSM-2225-25	32.0		36.0	15.0	GSM-3236-15
22.0		25.0	30.0	GSM-2225-30	32.0		36.0	20.0	GSM-3236-20
22.0		25.0	38.5	GSM-2225-38.5	32.0	+0.050	36.0	30.0	GSM-3236-30
24.0	+0.020 +0.072	25.0	25.0	GSM-2425-25	32.0	+0.150	36.0	40.0	GSM-3236-40
24.0	+0.040	27.0	6.0	GSM-2427-06	35.0		39.0	14.0	GSM-3539-14
24.0	+0.124	27.0	15.0	GSM-2427-15	35.0		39.0	20.0	GSM-3539-20

³⁾ 按壓組裝後 測試方法 ▶ 頁碼 57

iglidur® G | 產品範圍

軸襯套 (型號 S)

尺寸 [mm]

d1	d1- 公差 ³⁾	d2	b1 h13	產品型號	d1	d1- 公差 ³⁾	d2	b1 h13	產品型號
35.0		39.0	25.0	GSM-3539-25	60.0		65.0	30.0	GSM-6065-30
35.0		39.0	30.0	GSM-3539-30	60.0		65.0	40.0	GSM-6065-40
35.0		39.0	40.0	GSM-3539-40	60.0	+0.060	65.0	50.0	GSM-6065-50
35.0		39.0	50.0	GSM-3539-50	60.0	+0.180	65.0	60.0	GSM-6065-60
35.0		41.0	50.0	GSM-3541-50	60.0		65.0	70.0	GSM-6065-70
36.0		40.0	20.0	GSM-3640-20	62.0	+0.100	67.0	35.0	GSM-6267-35
37.0		41.0	20.0	GSM-3741-20	62.0	+0.250	67.0	72.0	GSM-6267-72
38.0		42.0	25.0	GSM-3842-25	62.0		70.0	30.0	GSM-6570-30
40.0		44.0	10.0	GSM-4044-10	65.0		70.0	50.0	GSM-6570-50
40.0		44.0	16.5	GSM-4044-16	65.0		70.0	104.0	GSM-6570-104
40.0		44.0	20.0	GSM-4044-20	68.0		73.0	60.0	GSM-6873-60
40.0		44.0	30.0	GSM-4044-30	70.0	+0.060	75.0	60.0	GSM-7075-60
40.0		44.0	40.0	GSM-4044-40	72.0	+0.180	77.0	24.5	GSM-7277-24.5
40.0		44.0	50.0	GSM-4044-50	72.0		77.0	76.0	GSM-7277-76
40.0	+0.050	44.0	52.5	GSM-4044-525	75.0		80.0	40.0	GSM-7580-40
42.0	+0.150	46.0	40.0	GSM-4246-40	75.0		80.0	60.0	GSM-7580-60
44.0		48.0	20.0	GSM-4448-20	80.0		85.0	60.0	GSM-8085-60
45.0		50.0	10.0	GSM-4550-10	80.0		85.0	100.0	GSM-8085-100
45.0		50.0	20.0	GSM-4550-20	85.0		90.0	100.0	GSM-8590-100
45.0		50.0	22.0	GSM-4550-22	90.0		95.0	100.0	GSM-9095-100
45.0		50.0	23.5	GSM-4550-235	95.0		100.0	100.0	GSM-95100-100
45.0		50.0	30.0	GSM-4550-30	100.0		105.0	21.5	GSM-100105-21.5
45.0		50.0	38.0	GSM-4550-38	100.0	+0.072	105.0	30.0	GSM-100105-30
45.0		50.0	40.0	GSM-4550-40	100.0	+0.212	105.0	32.0	GSM-100105-32
45.0		50.0	50.0	GSM-4550-50	100.0		105.0	100.0	GSM-100105-100
50.0		55.0	20.0	GSM-5055-20	105.0		110.0	100.0	GSM-105110-100
50.0		55.0	25.0	GSM-5055-25	110.0		115.0	100.0	GSM-110115-100
50.0		55.0	30.0	GSM-5055-30	120.0		125.0	100.0	GSM-120125-100
50.0		55.0	40.0	GSM-5055-40	125.0		130.0	100.0	GSM-125130-100
50.0		55.0	50.0	GSM-5055-50	130.0		135.0	100.0	GSM-130135-100
50.0		55.0	60.0	GSM-5055-60	135.0	+0.085	140.0	80.0	GSM-135140-80
52.0		57.0	20.0	GSM-5257-20	140.0	+0.245	145.0	100.0	GSM-140145-100
55.0		60.0	20.0	GSM-5560-20	140.0		145.0	104.0	GSM-140145-104
55.0	+0.060	60.0	40.0	GSM-5560-40	150.0		155.0	100.0	GSM-150155-100
55.0	+0.180	60.0	50.0	GSM-5560-50					
55.0		60.0	60.0	GSM-5560-60					

³⁾ 按壓組裝後

測試方法 ► 頁碼 57